



## LTE700 IR Pass Distn Amp 2 Way

Art. Number 334091



### LTE 700 2 Way IR Pass Amplifier

- LTE700 protected IR Pass Distribution Amplifier
- Distributes to multiple TV's around the home
- Allows control of Sky Digital receivers when used with TRIAX Digital Links and MOD103T Modulator
- 1 Input 2 Output
- Short circuit protected in each output
- Power on LED
- Screened housing
- F-Connectors
- Easy to mount fixing

## Technical Specifications

### ORDER INFORMATION

EAN Number 5702663340916

### CHARACTERISTICS

Max. Output level | dB $\mu$ V 94.0 dB $\mu$ V

### FREQUENCY RANGE

Output frequency range | MHz 85...694 MHz  
Frequency range UHF | MHz 470...694 MHz  
Frequency Range FM | MHz 87.5...108 MHz  
Frequency Range DAB | MHz 217...230 MHz  
Frequency range VHF | MHz 85...230 MHz

### GAIN

Gain | dB 10 +/-2 dB  
Noise figure | dB <5 dB

### ELECTRICAL

Impedance |  $\Omega$  75  $\Omega$



## Technical Specifications

### OPERATIONAL

AC Supply voltage | VAC 230 ±10% / 50Hz VAC

### CONNECTORS

Number of inputs 1

Number of outputs 2

### MECHANICAL

Colour RAL 7016 - Anthracite grey

Packing QTY 1

Packaging Height | m 0.060 m

Packaging Width | m 0.185 m

Packaging Depth | m 0.125 m

Packaging Volume | m3 0.001 m3

Net Weight | kg 0.425 kg

Tara Weight | kg 0.090 kg

Total Weight | kg 0.515 kg

Remarks fully screened within plastic housing