



LTE700 IR Pass Distn Amp 4 Way

Art. Number 334092



LTE 700 4 Way IR Pass Amplifier

- LTE700 protected IR Pass Distribution Amplifier
- Distributes to multiple TV's around the home
- Allows control of Sky Digital receivers when used with TRIAX Digital Links and MOD103T Modulator
- 2 Input 4 Output
- Short circuit protected in each output
- Power on LED
- Screened housing
- F-Connectors
- Easy to mount fixing

Technical Specifications

ORDER INFORMATION

EAN Number 5702663340923

CHARACTERISTICS

Max. Output level | dB μ V 94.0 dB μ V

FREQUENCY RANGE

Output frequency range | MHz 85...694 MHz
Frequency range UHF | MHz 470...694 MHz
Frequency Range FM | MHz 87.5...108 MHz
Frequency Range DAB | MHz 217...230 MHz
Frequency range VHF | MHz 85...230 MHz

GAIN

Gain | dB 10 +/-2 dB
Noise figure | dB <5 dB

ELECTRICAL

Impedance | Ω 75 Ω



Technical Specifications

OPERATIONAL

AC Supply voltage | VAC 230 ±10% / 50Hz VAC

CONNECTORS

Number of inputs 2

Number of outputs 4

MECHANICAL

Colour RAL 7016 - Anthracite grey

Packing QTY 1

Packaging Height | m 0.060 m

Packaging Width | m 0.225 m

Packaging Depth | m 0.125 m

Packaging Volume | m³ 0.002 m³

Net Weight | kg 0.485 kg

Tara Weight | kg 0.090 kg

Total Weight | kg 0.575 kg

Remarks fully screened within plastic housing